



SciDome System

Startup & Shutdown Procedures

Recommended **Startup** order:

1. Turn ON keyswitch and wait 1 minute before next step.
2. Press computer power button for Preflight, Renderbox and eMedia (if installed) to boot up.
 - a. Note Power LEDs are ON.
3. Wait for Windows to launch and All applications to auto launch.
4. Power on the SciDome Projector(s) once ATM-4 is running.
5. Wait for Projector(s) to warm up (15 to 20 min. for dual projectors) and confirm StarryNight or another application is displayed on the dome.
6. Turn ON Sound system and adjust volume accordingly.
7. SciDome system is ready for use.

Recommended **Shutdown** order:

1. Turn OFF Sound System, or to Standby or Lower the volume.
2. Turn OFF SciDome Projector(s) via ATM-4.
 - a. Confirm Projector Lamp(s) are off and unit(s) in standby.
3. Properly Exit All Applications on Preflight and Renderbox.
 - a. Quit StarryNight Renderbox and The Layered Earth if prompted.
4. Exit ATM-4 on Preflight, if not already closed.
5. Shutdown Preflight & Renderbox computers via "shutdown all" icon on Preflight desktop.
 - a. eMedia will shutdown if installed.
6. Wait for ALL computers to shutdown.
 - a. Make sure the Power LEDs are OFF.
7. DO NOT KEY OFF the system yet!
8. Wait for Projector cool down (up to 15 minutes) and confirm computers are OFF.
9. Confirm all steps have been completed prior to KEY OFF of the system.
10. Turn OFF keyswitch.